



Description: Head Lights
Part Number: 111031-111032-111097-
Application: Ford F150 1997-2003 / Ford Expedition 1997-2002



Tools needed: Phillips screwdriver, T20 Torque screw, wire splicer, electrical tape.



Step 1: Remove the eight plastic screws holding in the plastic cover shroud.



Step 2: Pull up the two locking pins holding in the headlight.



Step 3: Pull off the headlight assembly straight out from the car and unplug the headlight harness.



Step 4: Use the t20 torque screw to remove the screw holding in the corner light. Located at the top of the corner light



Step 5: Remove the bulb from the corner light.



Step 6: Remove corner bulb out from the harness.



Step 7: Splice in the halos into the corner light. Halo wires are two red one power and the other wire ground. Splice one red wire (+) positive into the brown wire on the corner light. Other red wire (-) negative will be spliced into the black wire on the corner light.

Step 8: Splice the led wires into the corner light. Blue wire (+) will be positive splice into the brown wire on the corner light. Black wire (-) negative will be spliced in to the black wire on the corner light.

Step 9: Plug in the headlight harness into the new Anzo headlight assembly.



Step 10: Align the headlight and place back into housing.



Step 11: Test all functions making sure they are working properly before driving.

AnzoUSA™ products are covered, by a limited one (1) year warranty, to be free of manufacturer's defects. However, certain AnzoUSA™ product categories have warranty policies which differ from this standard, please contact your representative for detailed category information. Damage due to improper installation or road hazards is not covered. Seller and manufacturers' only obligations shall be to replace the product proven to be defective. Neither seller nor manufacturer shall be liable for any injury, loss or damage, direct or consequential, arising out of the use of or the inability to use the product. Before using, user shall determine the suitability of the product for its intended use, and user assumes all risk and liability whatsoever in connection therewith.